



Key Features

Fully compliant to BS8300:2009



Remote indication of up to four zones



Light grey finish double gang plate



Blue LED “halo” Braille-enhanced Accept button



Individually monitored lines with lamp test facility



Overview

All building owners carry the responsibility of ensuring the safety of everyone inside, particularly those with limited mobility. Building regulations mandate the installation of suitable emergency assistance alarm systems in specific areas, like accessible bathrooms, enabling users to seek aid if necessary.

Emergency Voice Communication (EVC) systems empower individuals to issue alerts or request assistance during emergencies, typically aiding those with disabilities or mobility challenges.

Among EVC systems, Crisis Assist stands out, offering building owners a fully compliant and adaptable solution with numerous advantages. These include clear signalling, audio and visual feedback, and sleek stainless steel finishes that seamlessly integrate into any environment.

Crisis Assist Disabled Toilet Alarm Controller, 4 Lines

The Crisis Assist Disabled Toilet Alarm Controller is designed to enable the continual monitoring of up to four lines, or zones, and allow the acceptance of assistance calls.

The controller should be located in a permanently staffed area of the premises where assistance calls can be received and actioned as quickly as possible. The controller features an integrated buzzer for audio alert as well as a unique blue “halo” indicator around the Accept button which initially flashes for visual indication of a call; this then turns solid once accepted and the buzzer is muted.

Tech Specs

Standards	BS8300:2009 Building Regulations Approved Document M: 2010
Cabling	Two core 0.4mm to 2.5mm CSA (max return resistance 10 Ohms)
Relay Output	30V 1A NO Volt Free
Alarm Output	50-80dBA
Dimensions (W x H)	146mm x 86mm
Back Box Information	25-35mm deep double gang flush or round corned metal surface box

Ordering Information

Part Number	Description
36-423	Crisis Assist Disabled Toilet Alarm Controller, 4 Lines